


# DA-FM2100 INSTALLATION MANUAL





This manual is intended for the users of the DA-FM2100 mounting bracket. It includes the instructions for mounting the DA-FM2100.



- **This bracket is intended to be used with DC-I6212WRX model. Ask your retailer for details on a specific model and do not use it with other models of cameras.**
- **This installation should be performed by a qualified service personnel in conformance to all local codes.**
- **You may need to reinforce the wall. If the wall is not strong enough to support the product, the product may fall.**
- **Do not use this product for other purposes.**

## Mounting





- When installing in a 4-gang electrical box (not provided)
- When installing on a regular wall (ensuring a depth of at least 40mm and a size of at least 178.8mm x 65.8mm for the main body insertion part), use a flush mount to create an insertion space.
- When installing on a regular wall, use the 4 provided screws and anchors with DC-I6212WRX.


- 1 Attach the cable connection and installation plate to the Intercom (DC-I6212WRX) main body.




When inserting the intercom body with cable connection completed into the back hole of the flush mount, insert it vertically as shown in the picture below.





Install with attention to the **UP** direction, as shown in the picture below.




- 2 Fasten the 2 provided screws on the back.



- 3 Secure the intercom body and flush mount with 4 screws (not provided). Fasten 4 screws that match the screw hole dimensions (Ø4.5).
- 4 Finish securing the flush cover over the installation.



Fasten while pushing down on the 4 hooks. When fastening the hook, make sure to do it with attention to the **UP** direction.



## Dimensions

Unit: mm

